

An ISO 3297: 2007 Certified Organization

Volume 4, Special Issue 11, September 2015

National Conference on Emerging Trends in Computing, Communication & Control Engineering [NCET 2K15]

On 4th September, 2015

Organized by

Department of CSE, ECE & EEE, Magna College of Engineering, Chennai-600055, India.

A SEPIC Based Dual Output DC-DC Converter for Solar Applications

P.Ponuthai¹, S.Saravanan², Dr. P.Usharani³

Student, Dept. of EEE, Magna College of Engineering, Magaral, Chennai, Tamilnadu, India


Assistant Professor, Dept. of EEE, Magna College of Engineering, Magaral, Chennai, Tamilnadu, India

Professor, Dept. of EEE, R.M.D Engineering College, Chennai, Tamilnadu, India³

ABSTRACT: This paper presents the topic on obtaining dual output from the single input source. Here we using the combination of single ended primary inductance converter and high gain multilevel boost converter. One output is obtained from sepic converter and the other output is obtained from high gain multilevel boost converter. High gain multilevel boost converter is used for the step up purpose and the sepic converter is used as the step up or step down purpose depending upon the duty cycle applied to the switch. If the duty cycle is below 0.5 it works for step down purpose and if it is greater than 0.5 it works for step up purpose. Here the duty cycle applied to the switch is 0.75 hence for step up purposed. The input applied to the converter is 12V and the output from the sepic is 33V and from the boost converter is 220V. The simulation results are obtained in MATLAB/SIMULINK.

I. INTRODUCTION

Electricity generation from renewable energy is increasing day to day. The electricity generated from fossil fuels causes rising of toxic gases in the atmosphere but these are decreasing largely in the environment. Solar energy is one of the most abundant renewable energy resource, eco-friendly, and pollution free. Sun light is converted into electricity via solar cell using the photovoltaic effect. For solar energy system installation cost only needed, if once installed it can run for a long duration and it can also save the overall maintenance cost. Solar energy having versatile in nature, it can be used for different power applications from tiny torch to satellite. Dual converters are useful when dual output voltage levels are required from single input supply voltage. Flyback converter is capable to produced dual output voltage levels but it required transformer. The gain of flyback converter is depends upon the turns ratio of transformer. Sepic converter is used for step up step down application. High gain multi level boost converter is used to step up the voltage level with large conversion ratio. More number of switches and elements are required for generating dual output voltage level from conventional converters. Due to increases in number of switches and elements, converter circuit becomes more expensive and complex sepic based dual output converter is proposed which is suitable for solar applications. The proposed converter topology is the combination of sepic and high gain multilevel DC-DC boost converter. High gain multilevel DC-DC boost converter combines the conventional boost converter and voltage multiplier functions. The gain of voltage multiplier circuit can be increases by adding diodes and capacitors. Circuit diagram of boost converter, voltage multiplier and sepic converter are depicted in Fig1. The main advantages of proposed circuit topology are (i) dual output (ii) transformer less based design (iii) single switch.





An ISO 3297: 2007 Certified Organization

Volume 4, Special Issue 11, September 2015

National Conference on Emerging Trends in Computing, Communication & Control Engineering [NCET 2K15]

On 4th September, 2015


Organized by

Department of CSE, ECE & EEE, Magna College of Engineering, Chennai-600055, India.


II. CIRCUIT DESCRIPTION

A. Powercircuit

Power circuit diagram of proposed sepic based dual output DC-DC converter is depicted in Fig2. In the proposed converter only one input source and switch is required to obtain two output voltages at the same time. One output voltage is obtained through 5-level multi level boost converter and other output voltage is obtained through sepic converter. Sepic converter operates in two modes, step-up or step-down depending on duty cycle. When duty cycle is less than 0.5, sepic converter is operated **in** step-down mode. When duty cycle is greater than 0.5, sepic converter is operated in step-up mode. The output voltage levels of high gain multi level boost converter can be increases by adding diodes and capacitors without disturbing main sepic converter circuit.



CIRCUIT DIAGRAM



B. Modes of operation

The operation of the sepic based dual output DC-DC converter can be divided into two modes, when switch S is tuned ON and another when switch S is turned OFF. In mode1, switch S is tuned ON, the inductors L and L2 are discharges through the input source and capacitor Cs1 respectively. Capacitor CI clamps the voltage across capacitor C2 through D2 and switch S, when D2 is forward biased. Voltage VC\+VC3 clamp



An ISO 3297: 2007 Certified Organization

Volume 4, Special Issue 11, September 2015


National Conference on Emerging Trends in Computing, Communication & Control Engineering [NCET 2K15]

On 4th September, 2015

Organized by

Department of CSE, ECE & EEE, Magna College of Engineering, Chennai-600055, India.

the voltage VC2+VC4 through 04 and Switch S, when D4 is forward biased .Voltage across voltageVCZ+VC4+VC6 is clamp by voltage VC\+VC3+VCS through 06 and switchS, when D6 is forward biased. Similarly voltage VCZ+VC4+VC6+VCS is clamp by VCi+VC3+VCS+VC7 through Ls and switch S, when D8 is forward biased. The current direction and operating modes, when switch is tuned ON is shown in Fig.3 (a-e)In mode 2, switch S is turned OFF, the inductors L_1 and L_2 are discharges through D and D₁. Capacitors of the sepic converter C_{S1} and C_{S0} are charges from the input voltage VC\+VC3. Voltage VC\+VC3+VC3 is clamp by voltage V\N+VU+VC2 clamps the voltage VC\+VC3. Voltage VCI+VC3+VCS is clamp by voltage VTN+VU+VC2+VC4 through Os, when 05 is forward biased. When 07 is forward biased, voltage TN+Vu+VC2+VC4+VC6 is clamp the voltage VC\+VC3+VC3+VC5+VC7 through 07. Similarly, when 09 is forward biased, voltage VCI+VC3+VC3+VC3+VC7+VC9 is clamp by voltage VIN+VC2+VC4+VC6 through 09. The current direction and operating modes, when switch is turned OFF is shown in Fig A (a-e).



ANALYSIS OF PROPOSED CONVERTER

When switch S is closed, both inductors L1 and L2 will charges from input voltage and capacitor Csi respectively

 $V_{L1} = V_{IN}$ (1) $V_{L2} = -V_{CSI}$ (2)Voltage VC2 is charges from voltage V_{c1} $V_{c1} = Vc_2$ Similarly, $Vc_{1}+V_{c2} = Vc_{2}+V_{c4}$ $V_{c1}+V_{c3}+V_{c5}=V_{c2}+V_{c4}+V_{c6}$ $V_{c1}+V_{c3}+V_{c5}+V_{c7}=V_{c2}+V_{c4}+V_{c6}+V_{c8}$ When switch S is open, both inductors will discharges $V_{L1} = V_{IN} - V_{cs1} - V_{02}$ $V_{L1} = V_{IN} - V_{c1}$ (9) $V_{L2} = V02$ By inductor volt second balance for inductor L1,



An ISO 3297: 2007 Certified Organization

Volume 4, Special Issue 11, September 2015

National Conference on Emerging Trends in Computing, Communication & Control Engineering [NCET 2K15]

On 4th September, 2015

Organized by

Department of CSE, ECE & EEE, Magna College of Engineering, Chennai-600055, India.

 $\begin{aligned} & V_{L1}(\mathbf{D}) + V_{L1}(\mathbf{I}-\mathbf{D}) = \mathbf{0} \\ & \text{From equation (1) and (7)} \\ & V_{IN}(\mathbf{D}) + (V_{IN}-V_{CS1}-V_{02})(\mathbf{I}-\mathbf{D}) = \mathbf{0} \\ & V_{IN} + (-V_{CS1}-V_{02})(1-\mathbf{D}) = \mathbf{0} \\ & V_{C^{-1}}/V_{IN} = 1/(1-\mathbf{D}) \\ & \text{By inductor volt second balance for inductor L2,} \\ & V_{L2}(\mathbf{D}) + V_{L2}(\mathbf{I}-\mathbf{D}) = \mathbf{0} \\ & -V_{CS1}(\mathbf{D}) + V_{02}(1-\mathbf{D}) = \mathbf{0} \\ & V_{CS1} = V_{02}(1-\mathbf{D})/\mathbf{D} \\ & \text{Put } v_{CS1} \text{ in equation (12)} \\ & V_{IN} - (V_{02}(1-\mathbf{D})/\mathbf{D} + V_{02}) (1-\mathbf{D}) = \mathbf{0} \\ & V_{02}/V_{IN} = \mathbf{D}/(1-\mathbf{D}) \end{aligned}$

= 0

 $\begin{array}{l} V_{01} = v_{C1} + v_{C3} + v_{C7} + v_{C9} \\ V_{01} = 5 v_{C1} \\ \text{Thus, the conservation ratio of proposed converter is} \\ V_{01}/V_{IN} = 5/(1-D) \\ V_{02}/V_{IN} = D/(1-D) \\ \text{For N-level boost converter voltage gain is} \\ G_{01} = N/(1-D) \\ \text{For sepic converter voltage gain is} \\ G_{02} = D/(1-D) \end{array}$

Thus, voltage gain for is depends upon duty cycle and the number of levels present in multiplier and voltage gain for load2 depends upon duty cycle only

III. SIMULATION RESULTS

The proposed converter is designed for 12V input supply with rated output parameters 180W, 230V and 50W, 36V. Switching frequency of applied gate pulse is 50KHz with 75% duty cycle. Simulation results of proposed converter are verified through MATLAB/SIMULINK. Table shows the specification of proposed converter.

N0	Parameter	Value
1	Input voltage	12V
2	O/p voltage (v_{01}) and	230V and 36V
	(V ₀₂)	
3	Power (P_{01}) and (P_{02})	180Wand50W
4	Inductor (L_1) and (L_2)	700lH
5	capacitors	2201F
6	Switching frequency	50KHz
7	Duty cycle	75%
8	Number of Level in	5level
	boost converter	

Tabled Specification of converter

Graph of voltage gain versus duty cycle is shown in Fig5. Output voltage and output current waveform for load1 is shown in Fig6. Output voltage and output current wave form for load2 is shown in Fig7. Voltage stress across switch is 48V which is shown in Fig8. Output power wave form for load and load 2 is shown in Fig9. The current wave form through inductors with applied gate pulse is shown in Fig10. It is observed that



An ISO 3297: 2007 Certified Organization

Volume 4, Special Issue 11, September 2015


National Conference on Emerging Trends in Computing, Communication & Control Engineering [NCET 2K15]

On 4th September, 2015

Organized by

Department of CSE, ECE & EEE, Magna College of Engineering, Chennai-600055, India.

their sepic inductors current waveform is 0.3A. The voltage at output capacitors node is shown in Figll



IV. CONCLUSION

The proposed sepic based dual output DC-DC converter is designed for solar application where two output voltages is needed at the same time. The converter was designed to supply 230V at 180W for load1 and 36V at 50W from supply input 12V. The proposed converter is designed by the combination of sepic converter and five level multi level boost converters. Voltage gain for load is depends upon duty cycle and the number of levels present in multiplier and voltage gain for load2 depends upon duty cycle only. The proposed



An ISO 3297: 2007 Certified Organization

Volume 4, Special Issue 11, September 2015

National Conference on Emerging Trends in Computing, Communication & Control Engineering [NCET 2K15]

On 4th September, 2015

Organized by

Department of CSE, ECE & EEE, Magna College of Engineering, Chennai-600055, India.

converter simulation results are verified by using MATLAB/SIMULINK. The simulation results show that the proposed converter is suitable for solar application where two output voltages are needed at the same time.

REFERENCES

- 1. Rong-JongWai, Wen-HungWang, ChungYouLin, "High Performance Stand-Alone Photovoltaic Generation System" IEEE Transactions on Industrial Electronics, vol.55, no.1, pp.240-250, Jan.2008.
- MahrousE.Ahmed, MustafaMousa "Development of high gain and efficiency photovoltaic system using multilevel boost converter topology" 2. 2010 2nd IEEE International Symposium on power Electronic for Distributed Generation System.
- YiZhao, WuhuaLi, VanDeng, XiangningHe "Review of Non Isolated High Step-Up DC-DC Converters in Photovoltaic Grid Connected 3. Applications" IEEE Transactions on Industrial Electronics, vol.PP, no.99, pp.1-1, 2010
- CharanasomboonT, DevaneyMJ, andHotR.G, "Single switch dual output DC-DC converter"Industry Application Society Annual Meeting, 4. IEEE, Vol.1, pp.793-795, 1988.
- Wing HungKi, and DongshengMa, "Single-inductor multiple output switching converters" Power Electronics Specialists Conference, 5. PESe.2001,vol.3,pp.301-304,6-9 May.2001
- 6. Kanthaphayao Y, Rungruenngphalanggul Y, and Chaisawadi A, "Dual output DC-DC power supply with Buck-Boost and Zeta converter" International Conference on Control Automation and systems, pp.1154-1158,2002

7

- N.Vazquez, H.Lopez, C.Hernandez, H.Callej "Multiple Output DC-DC based on the Fly back Converter" 2008IEEE. M.Vazquez, E.delaCruz, J.A.NavasandJ.A.Cobos "Fixed Frequency Forward Flyback Converter with 8. with Two Fully Regulated Outputs"Telecommunications Energy Conference, INTELEC'95, 17th International, pp.161-166, 1995.
- 9. Huiming Chen, Wenhui Dong, Ying yan Heand Zhaoming Qian "Secondary Side Post Regulation Application in Multiple Outputs Flyback Converter" and the second secondIEEEPEDS 2005.
- 10. Ki-BumPark, Hyun-WookSeong, Hyoung-SukKim, Gun-WooMoon, andMyung-JoongYoun"IntegratedBoost-SepicConverterfor High StepupApplications"2008IEEE.
- Seung-PilMun, Jin-TaeKim, Su-JhJang, Chung-YuenWon" ANewSepic-FlybackConverter" Conference of the IEEE industrial 11. Soo-SeokKim, ElectronicsSociety2004.
- 12. JulioCesarRosas-Caro, JonathanCarlosMayo-Maldonado, RubenSalas-Cabrera"AFamilyofDC-DCMultiplierConverters"Advanceonlinepublication: 10February2011.
- 13. RosasCaro, T.e.; Ramirez, T.M.; Peng, F.Z.; Valderrabano, "ADC-DC multilevel boost converter, "IET Power Electronics.vol.3, no.l, pp.129-137, 2010.